# **HD Conference Dome**

www.boschsecurity.com





- ▶ HD 1080p and 720p resolutions
- ▶ 160x zoom (10x optical, 16x digital)
- ▶ Industry standard HD-SDI output
- ► Control and configuration via Ethernet
- ➤ Screen line option for displaying delegate names up to 16 characters

The HD Conference Dome is an extremely compact and easy to install PTZ camera with an industry standard HD-SDI output for superb HD quality video.

The camera provides complete network-based control of all dome functionality including pan/tilt/zoom operation, presets as well as web-based configuration of all dome settings.



## **Notice**

# Use of Camera

The HD Conference Dome is designed for use in conferencing applications only.

## **HD Conference Dome highlights**

With a dome diameter of only 5.04 inches (12.8 cm), the HD Conference Dome is nearly 50% smaller than the Bosch AutoDome. These compact dimensions make the HD Conference Dome ideal for conference environments.

Despite its compact design, the HD Conference Dome delivers state-of-the-art technology and features that are rare to most compact PTZ cameras. Its variable

pan and tilt speeds and AutoPivot ensure optimal camera control and viewing at all zoom levels. The high-performance 160x (10x optical/16x digital) zoom autofocus camera incorporates the latest digital imaging technology with excellent sensitivity and resolution. With 64 user-defined presets the HD Conference Dome is not small on features.

The HD Conference Dome maximizes your conference investment by integrating with Bosch conference systems including the DCN Next Generation conference system, as well as the DCN Wireless discussion system.

The HD Conference Dome is simple to install and use; available with surface, wall, recessed, and pipe mount options.

#### **System overview**

# High-performance 160x PTZ day/night camera

The HD Conference Dome PTZ camera has a 1/2.5-inch progressive scan CMOS sensor. With up to 1080p resolution and sensitivity to below 1.0 lux, the HD Conference Dome offers exceptional performance at a very affordable price.

Pan and tilt preset repeatability are accurate to within ±0.1 degrees to ensure that the correct scene is captured every time. The HD Conference Dome delivers variable pan/tilt speeds from a crawl speed of only 1 degree per second up to an ultra-quick 120 degrees per second. The dome is capable of pan speeds of 360 degrees per second and tilt speeds of 100 degrees per second between prepositions. The HD Conference Dome provides a tilt range of 0 to 94 degrees, and a pan range of up to 360 degrees continuous rotation.

The AutoScaling (proportional zoom) and AutoPivot (automatically rotates and flips the camera) features ensure optimal control.

# **Industry standard HD-SDI output**

The HD Conference Dome makes use of an industry standard HD-SDI output for superb HD quality video. The HD Conference Dome supports 1080p30 and 720p60 resolutions for 50 Hz and 60 Hz models at 16:9 aspect ratio.

#### Multiple video streams

Next to the HD-SDI output, Bosch's innovative Quadstreaming feature enables the HD Conference Dome to deliver three H.264 streams together with an M-JPEG stream in full and reduced bandwidth modes for monitoring purposes.

#### Image stabilization

Image stabilization algorithms included with the HD Conference Dome reduces camera shake in both the vertical and horizontal axis, resulting in exceptional image clarity. Bosch's unique image stabilization solution does not reduce camera sensitivity, unlike competitive systems.

## **Unsurpassed reliability**

As with all Bosch products, the camera is designed using the industry's best design process and is subjected to the most stringent testing standards such as HALT (highly accelerated life testing).

## **Functions**

The following are some of the features that make the HD Conference Dome the perfect fit for a variety of conference applications.

## Network-based control and configuration

The HD Conference Dome enables full camera control and configuration capabilities over the network. Operators or technicians can control camera pan/tilt/zoom operation, and presets virtually anywhere without need for additional wiring.

The embedded web server lets the installer access all the user settings, make camera adjustments, and update firmware via a standard web browser or via the Bosch Video Management System.

## **Device management**

Simple Network Management Protocol (SNMP) support facilitates the remote monitoring and management. The HD Conference Dome provides full support for SNMP v3.

#### Ease of installation and servicing

The HD Conference Dome has been designed for quick and easy installation. The dome comes fully assembled and ready for surface mount applications. Also available are wall, recessed, and pipe mounting kits which allow the HD Conference Dome to be easily adapted for the individual site requirements.


#### **Power over Ethernet**

Power for indoor camera models may be supplied via a Power over Ethernet Plus (PoE+, IEEE 802.3at, class 4) compliant network cable connection. With this configuration, only a single cable connection is required to power and to control the camera while also monitoring images from the camera via the web server. An additional coax cable is required for the video from the HD-SDI output.


## **Certifications and approvals**

| Electromagnetic<br>Compatibility (EMC) | Complies with FCC Part 15, ICES-003, and CE regulations      |
|--|--|
| Product Safety                         | Complies with CE regulations, UL, CSA, EN, and IEC Standards |


## Installation/configuration notes




**HD Conference Dome Dimensions** 





Pipe Mount Dimensions






Wall Mount Dimensions





In-Ceiling / Recessed Mount Dimensions



Surface Mount Dimensions

# **Parts included**

# **Technical specifications**

# 10x HD Camera

| Imager   | 1/2.5 inch progres   | ssive scan CMOS                           |
|--|--|---|
| Number of Pixels   | 2.1 Megapixels   |   |
| Aspect Ratio   | 16:9   |   |
| Lens   | 10x optical zoom (<br>(F1.8/F2.5 to clos                         |   |
| Focus  | Automatic with ma  | nual override                             |
| Iris   | Automatic with ma  | nual override                             |
| Field of View  | Horizontal: 5.5° to<br>Vertical: 3.1° to 29                      |   |
| Automatic Gain Control   | Normal, Medium, I  | ligh, Fixed                               |
| Synchronization  | Internal   |   |
| Aperture Correction  | On/Off   |   |
| Digital Zoom   | 16x  |   |
|  |  |   |
| Sensitivity(typical) <sup>1</sup>  | <b>30 IRE</b> <sup>2</sup>                                       | <b>50 IRE</b> <sup>2</sup>                |
| Sensitivity(typical)¹  Day Mode  | <b>30 IRE</b> <sup>2</sup>                                       | <b>50 IRE</b> <sup>2</sup>                |
|  | 30 IRE <sup>2</sup>  | <b>50 IRE</b> <sup>2</sup> 2.0 lx         |
| Day Mode   |  |   |
| Day Mode SensUP Off  | 1.2 lx   | 2.0 lx                                    |
| Day Mode  SensUP Off  SensUP On (64x)  | 1.2 lx   | 2.0 lx                                    |
| Day Mode  SensUP Off  SensUP On (64x)  Night Mode  | 1.2 lx<br>0.038 lx   | 2.0 lx<br>0.063 lx                        |
| Day Mode  SensUP Off  SensUP On (64x)  Night Mode  SensUP Off  | 1.2 lx<br>0.038 lx<br>0.06 lx                                    | 2.0 lx<br>0.063 lx<br>0.1 lx<br>0.0031 lx |
| Day Mode  SensUP Off  SensUP On (64x)  Night Mode  SensUP Off  SensUP On (64x)  Electronic Shutter Speed       | 1.2 lx<br>0.038 lx<br>0.06 lx<br>0.0018 lx                       | 2.0 lx<br>0.063 lx<br>0.1 lx<br>0.0031 lx |
| Day Mode  SensUP Off  SensUP On (64x)  Night Mode  SensUP Off  SensUP On (64x)  Electronic Shutter Speed (AES) | 1.2 lx<br>0.038 lx<br>0.06 lx<br>0.0018 lx<br>1x to 64x; 1/50 (1 | 2.0 lx<br>0.063 lx<br>0.1 lx<br>0.0031 lx |

|           | (adjustable R and B signals in Manual mode) |
|-----------|---|
| Day/Night | Monochrome, Color, Auto                     |
|           |   |

- 1. F1.8, 1/30 (1/25) shutter, maximum AGC.
- 2. Tinted bubble adds 0.8 f-stop loss.

# **Software Control**

| Camera Configuration | Via Internet Explorer Web browser<br>version 7.0 or later or Bosch<br>Configuration Manager |
|----------------------|---|
| Software Update      | Firmware upload   |

# Video

| HD-SDI    |            |
|-----------|------------|
| Standards | SMPTE 292M |

# Resolutions (H $\times$ V) and Frame Rates

| • Full HD/1080p | 1920 x 1080, 30 ips |
|-----------------|---------------------|
| • HD/720p       | 1280 x 720, 60 ips  |
| Data Rate       | 1.5 Gbit/s          |
| Video Delay     | 10 ms               |

# **Network Stream**

| Standards        | H.264 (ISO/IEC 14496-10), M-JPEG,<br>JPEG  |
|------------------|--|
| Streaming        | Individually configurable streams in H. 264 and M-JPEG, configurable frame rate and bandwidth; |
| • 1080p30        | One (1) H.264 1080p30 stream plus<br>one (1) M-JPEG and one (1) I-frame<br>stream              |
| • 720p60         | One (1) H.264 720p60 stream plus<br>one (1) M-JPEG and one (1) I-frame<br>stream               |
| GOP Structure    | IP, IBP, IBBP  |
| Data Rate        | 9.6 kbps to 6 Mbps   |
| Overall IP Delay | 240 ms   |
|                  |  |

# Resolutions (H x V) and Frame Rates

| Stream    | 1 |
|-----------|---|
| O G OGIII | - |

| • Full HD/1080p | 1920 x 1080, 30 ips |
|-----------------|---------------------|
| • HD/720p       | 1280 x 720, 60 ips  |

# Stream 23

| • SD/480p (WVGA) <sup>4</sup>                   | 854 x 480, 30 ips |
|---|-------------------|
| <ul> <li>SD/240p (WQVGA)<sup>4</sup></li> </ul> | 432 x 240, 30 ips |

- 3. Stream 1 must be set to 720p at 30 ips.
- 4. Images displayed in 16:9 aspect ratio.

| Network  |  |
|--|--|
| Protocols  | RTP, Telnet, UDP, TCP, IP, HTTP,<br>HTTPS, FTP, DHCP, IGMP V2/V3,<br>ICMP, ARP, SMTP, SNTP, SNMP, RTSP,<br>802.1x, iSCSI, DynDNS, UPnP |
| NTCIP Protocols                                  |  |
| CCTV Camera<br>Control                           | NTCIP 1205   |
| Application Layer                                | SNMP per NTCIP 1101:1996 & NTCIP 2301  |
| <ul> <li>Transport/Network<br/>Layers</li> </ul> | TCP/IP per NTCIP 2202:2001   |
| Sub-network Layer                                | PMPP (Point to Multi-Point Protocol)<br>per NTCIP 2101:2001 & NTCIP<br>2102:2003   |
| Ethernet   | 10-Base T/100 Base-TX, auto-sensing, half/full duplex, RJ45  |
| PoE+   | IEEE 802.3at, class 4  |
|  |  |

## Mechanical/Electrical

| Pan Range          | 0-360° continuous   |
|--------------------|---|
| Tilt Angle         | 0-93.6°   |
| Variable Speed     | Pan: 1°/s to 120°/s<br>Tilt: 1°/s to 100°/s               |
| Pre-position Speed | Pan:360°/s<br>Tilt: 100°/s                                |
| Preset Accuracy    | ± 0.1° typical  |
| Rated Voltage      | 24 VAC ± 10%, 50/60 Hz or<br>PoE+ (IEEE 802.3at, class 4) |
| Power Draw         | 17 W typical  |

# **Environmental**

| Operating<br>Temperature | -10°C to 30°C (14°F to 86°F)       |
|--------------------------|------------------------------------|
| Storage<br>Temperature   | -20°C to 60°C (-4°F to 140°F)      |
| Operating Humidity       | 0% to 90% relative, non-condensing |

## Miscellaneous

| Pre-positions          | 64   |
|------------------------|--|
| Screen Line            | Up to 16 characters (only standard ASCII character set can be used)  |
| Supported<br>Languages | English, German, Dutch, French, Italian,<br>Spanish, Portuguese, Polish, Russian,<br>Chinese, and Japanese |

#### **User Connections**

| Power                                       |  |
|---|--|
| <ul> <li>PoE+, Indoor<br/>Models</li> </ul> | RJ-45 100 Base-TX Ethernet PoE+ IEEE<br>802.3at, class 4 |
| <ul> <li>Camera, All<br/>Models</li> </ul>  | 24 VAC, 50/60 Hz   |
| Video                                       | BNC with HD-SDI output                                   |
| Control                                     | RJ-45 100 Base-TX Ethernet                               |

## Construction

| Size (Diameter x<br>Height) | 153.0 x 133.0 mm<br>(6.02 x 4.61 in.) |
|-----------------------------|---------------------------------------|
| Bubble Size                 | 128.0 mm (5.04 in.)                   |
| Weight                      | 1.92 kg (4.24 lb)                     |
| Material                    |                                       |
| <ul> <li>Housing</li> </ul> | Cast aluminum                         |
| • Bubble                    | Acrylic                               |
| Color                       | White or Charcoal                     |

# **Ordering information**

# VCD-811-IWT HD Conference Dome, White, with Tinted Bubble

White, 1080p HD indoor camera for use with video conference system, with tinted bubble Order number **VCD-811-IWT** 

# VCD-811-ICT HD Conference Dome, Charcoal, with Tinted Bubble

Charcoal, 1080p HD indoor camera for use with video conference system, with tinted bubble Order number VCD-811-ICT

## Accessories

## VJR-A3-IC AutoDome Junior HD Indoor Recessed Mount

Recessed mount for indoor camera applications that do not require IP54 or a plenum rating Order number VJR-A3-IC

# VJR-A3-SP In-ceiling Support Kit for AutoDome 700/800 Series and AutoDome Junior HD

Suspended ceiling support kit for AutoDome 700 and 800 Series and AutoDome Junior HD In-ceiling mounts Order number VJR-A3-SP

# VJR-A3-IC54 AutoDome Junior HD Plenum-rated and Outdoor Recessed Mount

Recessed mount required for indoor camera applications that must attain an IP54 or a plenum rating, and required for all recessed outdoor camera applications

Order number VJR-A3-IC54

#### **VEZ-A2-JC Surface Mount Adapter**

Charcoal adapter for AutoDome Junior surface installations

Order number VEZ-A2-JC

# **VEZ-A2-JW Surface Mount Adapter**

White adapter for AutoDome Junior surface installations

Order number VEZ-A2-JW

## **VEZ-A2-PC AutoDome Junior Pipe Mount**

Charcoal

Order number VEZ-A2-PC

#### **VEZ-A2-PW AutoDome Junior Pipe Mount**

White

Order number VEZ-A2-PW

#### VEZ-A2-WC AutoDome Junior Wall Mount

Charcoal

Order number VEZ-A2-WC

## **VEZ-A2-WW Wall Mount**

White

Order number VEZ-A2-WW

# VJR-SBUB2-CL AutoDome Junior HD Clear Bubble, Indoor

Order number VJR-SBUB2-CL

# VJR-SBUB2-TI AutoDome Junior HD Tinted Bubble, Indoor

Order number VJR-SBUB2-TI

## UPA-2450-60 Power Supply, 120 V, 60 Hz

Indoor power supply for camera. 120 VAC, 60 Hz In; 24 VAC, 50 VA Out  $\,$ 

Order number UPA-2450-60

#### UPA-2450-50 Power Supply, 220 V, 50 Hz

Indoor power supply for camera. 220 VAC, 50 Hz In; 24 VAC, 50 VA Out

Order number UPA-2450-50

#### Represented by:

# Americas:

Americas:
Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
security.sales@us.bosch.com
www.boschsecurity.us

# Europe, Middle East, Africa:

Bosch Security Systems B.V. P.O. Box 80002 P.O. Box 80002 5617 BA Eindhoven, The Netherlands Phone: + 31 40 2577 284 Fax: +31 40 2577 330 emea.securitysystems@bosch.com www.boschsecurity.com

#### Asia-Pacific:

Asia-Pacific:
Robert Bosch (SEA) Pte Ltd, Security
Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia

#### China:

China:
Bosch (Shanghai) Security Systems Ltd.
201 Building, No. 333 Fuquan Road
North IBP
Changning District, Shanghai
200335 China
Phone +86 21 22181111
Fax: +86 21 22182398 www.boschsecurity.com.cn

#### America Latina:

America Latina:
Robert Bosch Ltda Security Systems Division
Via Anhanguera, Km 98
CEP 13065-900
Campinas, Sao Paulo, Brazil
Phone: +55 19 2103 2860
Fax: +55 19 2103 2862
latam.boschsecurity@bosch.com
www.boschsecurity.com