FCP-320/FCH-320 Conventional Automatic Fire Detectors

www.boschsecurity.com







- ► High reliability of detection thanks to evaluation electronics
- ► Active adjustment of the threshold (drift compensation) if the optical sensor becomes dirty
- ► Activation of a remote external detector alarm display possible
- ▶ Mechanical removal lock (can be activated/deactivated)
- ▶ Dust-repellent labyrinth and cap construction

The FCP-320/FCH-320 Series Conventional Automatic Fire Detectors set new standards in fire detection technology through a combination of optical, thermal and chemical (gas) sensors and intelligent evaluation electronics. Their most impressive feature is their ability to prevent false alarms, as well as speed and accuracy of detection.

The enhanced operating voltage range of 8.5 V DC up to 30 V DC and the two variants with 820 Ω alarm resistor or 470 Ω alarm resistor enables the detector application with nearly all conventional fire panels.

Optical (scattered light measurement) Thermal max x - x Thermal - x - x Gifferential Chemical (gas measurement)					
Thermal - x - x differential Chemical x (gas	(scattered light	Х	Х	Х	-
differential Chemical x (gas	Thermal max.	-	Х	-	Х
(gas		-	Х	-	Х
	(gas	Х	-	-	-

System overview

Operating mode	Detector type			
	FCP- FCP- FCP- FCH- OC320 / OT320 / O320 / T320 / FCP- FCP- FCP- FCP- FCH-T320- OC320- OT320- O320- FSA / R470 R470 R470 FCH-T320- R470			
Combined	Х	х	-	-

Functions

The FCP-OC320 and FCP-OT320 Multisensor Detectors each combine two detection principles. All sensor signals are analyzed continually by the internal evaluation electronics and are linked with each other. If a signal combination fits the detector's programmed code field, an alarm is automatically triggered. By linking the sensors, the combined detectors can also be used in places where work carried out gives rise to light smoke, steam or dust.

Optical sensor (smoke sensor)

The optical sensor uses the scattered-light method. An LED transmits light to the measuring chamber, where it is absorbed by the labyrinth structure. In the event of a fire, smoke enters the measuring chamber and the smoke particles scatter the light from the LED. The amount of light hitting the photo diode is converted into a proportional electrical signal.

Thermal sensor (temperature sensor)

A thermistor in a resistance network is used as a thermal sensor; an analog-digital converter measures the temperature-dependent voltage at regular intervals.

When the maximum temperature of 54°C is exceeded (thermal maximum), or if the temperature rises by a defined amount within a specified time (thermal differential), the temperature sensor triggers the alarm status.

Chemical sensor (CO gas sensor)

The main function of the gas sensor is to detect carbon monoxide (CO) generated as a result of a fire, but it will also detect hydrogen (H) and nitrous monoxide (NO). The sensor signal value is proportional to the concentration of gas. The gas sensor delivers additional information to effectively suppress deceptive values.

Depending on the service life of the gas sensor, the OC 320 detector switches off the C sensors after five years of operation. The detector will continue to function as an O detector. The detector should then be exchanged immediately in order to be able to keep using the higher reliability of detection of the OC detector.

Special features

Detector type	Drift compensation		
	Optical unit	Gas sensor	
FCP-0C320 FCP-0C320-R470	X	Х	
FCP-OT320 FCP-OT320-R470	X		
FCP-0320 FCP-0320-R470	X		
FCH-T320 FCH-T320-R470 FCH-T320-FSA			

Certifications and approvals

The detectors comply with:

Detector type	EN54-5:2000/ A1:2002	EN54-7:2000/ A1:2002/A2:2006
FCP-OC320		•

FCP-0C320-R470		•
FCP-OT320	•	•
FCP-OT320-R470	•	•
FCP-0320		•
FCP-0320-R470		•
FCH-T320	•	
FCH-T320-R470	•	
FCH-T320-FSA	•	

Region	Regulate	ory compliance/quality marks
Europe	CPR	0786-CPR-20353 FCH-T320_FCH- T320-R470
	CPR	0786-CPR-20351 FCP-0320_FCP- 0320-R470
	CPR	0786-CPR-20355 FCP-OC320_FCP- OC320-R470
	CPR	0786-CPR-20352 FCP-OT320_FCP- OT320-R470
Germany	VdS	G 208001 FCP-0320R470
	VdS	G 208002 FCP-OT320R470
	VdS	G 208003 FCH-T320R470
	VdS	G 208004 FCH-T320-FSA
	VdS	G 208005 FCP-OC320R470
Europe	CE	FCP-/FCH-320
	CE	MSR 320
	CPD	0786-CPD-20354 FCH-T320-FSA

Installation/configuration notes

- Up to 32 detectors can be connected per primary line
- Maximum cable length: 1000 m, for J-Y(St) Y n x 2 x 0.6/0.8
- Country-specific standards and guidelines must be observed during the planning phase
- The detector can be painted (cap and base) and thereby adapted to the surrounding colour scheme; note the information in the Painting Instructions (Document Number F.01U.089.231

Installation/configuration notes in accordance with VdS/VDE/DIBt

- Planning for multisensor detectors follows the guidelines for optical detectors, unless a specific VdS planning guideline is available (see DIN VDE 0833 Part 2 and VDS 2095)
- The OC and OT types are planned using the guidelines for optical detectors if operated as optical detectors or as combined detectors; see DIN VDE 0833 Part 2 and VDS 2095
- When planning fire barriers according to DIBt, you have to use the FCH-T320-FSA; its characteristic curve corresponds to class A1R

Technical specifications Electrical	
Operating voltage	8.5 V DC to 30 V DC
Current consumption	< 0.12 mA
Alarm output	Increase in current
/ warm output	(alarm resistance 820 Ω or 470 Ω)
Indicator output	Open collector connects 0 V in the event of an alarm over $3.92~k\Omega$
Mechanics	
Individual display	LED red
Dimensions	
Without base	Ø 99.5 x 52 mm
With base	Ø 120 x 63.5 mm
Housing material	Plastic, ABS
Housing color	White, similar to RAL 9010, matt finish
Weight without/with packaging	Approx. 80 g / approx. 120 g
• FCP-OC320 / FCP-OC320 R470	O- Approx. 85 g / approx 130 g
Environmental condition	ns
Protection class as per EN 60529	IP 40, IP 43 with detector base with damp room seal
Permissible relative humidity	95% (non-condensing)
Permissible air speed	20 m/s
Permissible operating temperatur	re -20 °C to +50 °C
• FCP-0320/FCP-0320- R470	-20 °C to +65 °C
• FCP-OC320 / FCP-OC320 R470	010 °C to +50 °C
Planning	
Monitoring area	Max. 120 m² (Heed local guidelines!)
• FCH-T320/-R470/-FSA	Max. 40 m ² (Heed local guidelines!)
Maximum installation height	16 m (Heed local guidelines!)
• FCH-T320/-R470/-FSA	6 m (Heed local guidelines!)

Special features

Response sensitivity

· Optical part (in line

with EN 54-7)

FCP-0C320 / FCP-0C320-R470 <

0.23 dB/m

	FCP-OT320 / FCP-OT320-R470 < 0.19 dB/m FCP-O320 / FCP-O320-R470 < 0.16 dB/m
Thermal maximum part	>54 °C
Thermal rate-of-rise part (in line with EN 54-5)	FCH-T320: A2R FCH-T320-FSA: A1R
Chemical part	In ppm range
Color code	
• FCP-OC320 / FCP- OC320-R470	Blue ring
• FCP-OT320/FCP- OT320-R470	Black ring
• FCP-0320/FCP- 0320-R470	No marking
• FCH-T320/-R470/- FSA	Red ring

Ordering information

FCP-O320 Smoke detector optical

conventional technology, with 820 Ohm alarm resistor Order number FCP-0320

FCP-OT320 Multisensor detector optical/thermal

conventional technology, with 820 Ohm alarm resistor Order number FCP-OT320

FCP-OC320 Multisensor detector optical/chemical

conventional technology, with 820 Ohm alarm resistor Order number FCP-OC320

FCP-OC320-R470 Multisensor detector optical/chemical conventional technology, with 470 Ohm alarm resistor Order number FCP-OC320-R470

FCP-OT320-R470 Multisensor detector optical/thermal conventional technology, with 470 Ohm alarm resistor Order number FCP-OT320-R470

FCP-O320-R470 Smoke detector, optical

conventional technology, with 470 Ohm alarm resistor Order number FCP-0320-R470

FCH-T320 Heat detector, rate-of-rise

conventional technology, thermal differential/thermal maximum detector, with 820 Ohm alarm resistor Order number FCH-T320

FCH-T320-R470 Heat detector

thermal differential/thermal maximum detector, conventional technology, with 470 Ohm alarm resistor Order number FCH-T320-R470

FCH-T320-FSA Heat detector, DIBt protection closures

thermal differential/thermal maximum detector, conventional technology, with 820 Ohm alarm resistor Order number FCH-T320-FSA

Accessories

MS 400 B Detector base with Bosch logo

Bosch-branded detector base for surface mounted and flush-mounted cable feed Order number MS 400 B

MS 400 Detector base

Detector base for surface mounted and flush-mounted cable feed, not branded.
Order number MS 400

FAA-420-SEAL Damp room seal, 10 pcs

1 package = 10 pieces Order number FAA-420-SEAL

MSR 320 Base with relay, conventional

with a change-over relay (Form C)
Order number MSR 320

MSC 420 Base extension with damp room sealing

Extension for detector bases with surface-mounted cable feed

Order number MSC 420

MSS 300 Base sounder white

Control via C-point of the detector Order number MSS 300

MSS300-WH-EC Base sounder, white

Control through fire panel via interface Order number MSS300-WH-EC

FAA-420-RI-DIN Remote indicator for DIN application

For applications where the automatic detector is not visible, or mounted in false ceilings/floors. This version complies with DIN 14623.

Order number FAA-420-RI-DIN

FAA-420-RI-ROW Remote indicator

For applications where the automatic detector is not visible, or mounted in false ceilings/floors.

Order number FAA-420-RI-ROW

FMX-DET-MB Mounting bracket

Mounting bracket for installation in false floors Order number FMX-DET-MB

WA400 Wall bracket

Console for DIBt compliant mounting of detectors above doors etc., including detector base Order number **WA400**

MH 400 Heating element

usable at locations where the functional safety of the detector might be impaired by condensation Order number MH 400

SK 400 Protective cage

prevents damage
Order number **SK 400**

SSK400 Dust protection, 10pcs

(packing unit = 10 units)
Order number **SSK400**

TP4 400 Label plate small

(packing unit = 50 units)
Order number **TP4 400**

TP8 400 Label plate large

(packing unit = 50 units)
Order number **TP8 400**

FCP-320/FCH-320 Conventional Automatic Fire Detectors

	FCP-O320 Smoke detector optical	FCP-OC320 Multisensor detector optical/chemical	FCP-OT320 Multisensor detector optical/thermal
Detector type	optical	optical/chemical	optical/thermal
Operating voltage	8.5 V DC 30 V DC	8.5 V DC 30 V DC	8.5 V DC 30 V DC
Current consumption	< 0.12 mA	< 0.12 mA	< 0.12 mA
Protection category	IP 40, IP 43 with MSF 400	IP 40, IP 43 with MSF 400	IP 40, IP 43 with MSF 400
Permissible operating temperature	-20°C+65°C	-10°C+50°C	-20 °C +50 °C
Monitoring area	max. 120 m²	max. 120 m²	max. 120 m²
Maximum installation height	16 m	16 m	16 m
Alarm resistance	820 Ω	820 Ω	820 Ω
Color code	no marking	blue loop	black loop
For fire barriers conforming to DIBt, quality-controlled			-

	FCP-0320-R470 Smoke detector, optical	FCP-OC320-R470 Multisensor detector optical/chemical	FCP-OT320-R470 Multisensor detector optical/thermal
Detector type	optical	optical/chemical	optical/thermal
Operating voltage	8.5 V DC 30 V DC	8.5 V DC 30 V DC	8.5 V DC 30 V DC
Current consumption	< 0.12 mA	< 0.12 mA	< 0.12 mA
Protection category	IP 40, IP 43 with MSF 400	IP 40, IP 43 with MSF 400	IP 40, IP 43 with MSF 400
Permissible operating temperature	-20°C+65°C	-10 °C +50 °C	-20°C+50°C
Monitoring area	max. 120 m²	max. 120 m²	max. 120 m²
Maximum installation height	16 m	16 m	16 m
Alarm resistance	470 Ω	470 Ω	470 Ω
Color code	no marking	blue loop	black loop
For fire barriers conforming to DIBt, quality-controlled	-	-	-

	FCH-T320 Heat detector, rate-of- rise	FCH-T320-R470 Heat detector	FCH-T320-FSA Heat detector, DIBt protection closures
Detector type	thermal differential/thermal maximum	thermal differential/thermal maximum	thermal differential/thermal maximum
Operating voltage	8.5 V DC 30 V DC	8.5 V DC 30 V DC	8.5 V DC 30 V DC
Current consumption	< 0.12 mA	< 0.12 mA	< 0.12 mA
Protection category	IP 40, IP 43 with MSF 400	IP 40, IP 43 with MSF 400	IP 40, IP 43 with MSF 400
Permissible operating temperature	-20°C+50°C	-20 °C +50 °C	-20°C+50°C
Monitoring area	max. 40 m²	max. 40 m²	max. 40 m ²
Maximum installation height	6 m	6 m	6 m
Alarm resistance	820 Ω	470 Ω	820 Ω
Color code	red loop	red loop	red loop
For fire barriers conforming to DIBt, quality-controlled			•

Represented by:

Europe, Middle East, Africa: Bosch Security Systems B.V.
P.O. Box 80002
5600 JB Eindhoven, The Netherlands
Phone: + 31 40 2577 284
emea.securitysystems@bosch.com
emea.boschsecurity.com **Germany:** Bosch Sicherheitssysteme GmbH Robert-Bosch-Ring 5 85630 Grasbrunn Germany www.boschsecurity.com

North America: Bosch Security Systems, Inc. 130 Perinton Parkway Fairport, New York, 14450, USA Phone: +1 800 289 0096 Fax: +1 585 223 9180 onlinehelp@us.bosch.com www.boschsecurity.us

Asia-Pacific:
Robert Bosch (SEA) Pte Ltd, Security Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia